

## DS-PM1-I8O2-H RS485 wired Input Expander



DS-PM1-I8O2-H is a wired zone expander for AX Hybrid Pro control panel, which has 8 on-board zones and 2 on-board collector outputs. This zone expander communicates with control panel via high-speed RS-485, and the maximum distance between zone expander and control panel can be 900m. What's more, DS-PM1-I8O2-H has another high-speed RS-485 output for cascading the next zone expander, and the cable distance can be another 900m. In this way, wired input expander is suitable for small to medium applications, like villa, shop, office, hotel, .etc.

- 8 on-board wired zones
- 2 on-board collector outputs
- 1 power output for wired detectors
- 2 high-speed RS-485, supports wired input expander cascade mode



## ▪ Specification

Hardware features	
Alarm input	8
IO Output	2 (collector outputs, used as control signal of relay module)
Bus	2×RS485 (high-speed), 1 input for control panel connection and 1 output for expander cascading
Tamper-Proof	Support (front and rear)
Electrical characteristics	
Power supply	9-15VDC
Power consumption	Maximum current 119mA@12VDC; Quiescent current 45mA@12VDC;
Output Voltage	9-15VDC (Same voltage as power supply)
Output Current	Maximum 500mA
General	
Operation temperature	-10°C to 40°C
Operation humidity	10% to 90%
Shell material	Plastic
Dimension(WxHxD)	110mm*155mm*31mm
Weight	252.5g

## ▪ Available Model

DS-PM1-I802-H(海外标配)(样机),



Distributed by

**HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
overseasbusiness@hikvision.com

**Hikvision USA**  
T +1-909-895-0400  
sales.usa@hikvision.com

**Hikvision Australia**  
T +61-2-8599-4233  
salesau@hikvision.com

**Hikvision India**  
T +91-22-28469900  
sales@pramahikvision.com

**Hikvision Canada**  
T +1-866-200-6690  
sales.canada@hikvision.com

**Hikvision Thailand**  
T +662-275-9949  
sales.thailand@hikvision.com

**Hikvision Europe**  
T +31-23-5542770  
sales.eu@hikvision.com

**Hikvision Italy**  
T +39-0438-6902  
info.it@hikvision.com

**Hikvision Brazil**  
T +55 11 3318-0050  
Latam.support@hikvision.com

**Hikvision Turkey**  
T +90 (216)521 7070- 7074  
sales.tr@hikvision.com

**Hikvision Malaysia**  
T +601-7652-2413  
sales.my@hikvision.com

**Hikvision UK & Ireland**  
T +01628-902140  
sales.uk@hikvision.com

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
sale.africa@hikvision.com

**Hikvision France**  
T +33(0)1-85-330-450  
info.fr@hikvision.com

**Hikvision Kazakhstan**  
T +7-727-9730667  
nikia.panfilov@hikvision.ru

**Hikvision Vietnam**  
T +84-974270888  
sales.vt@hikvision.com

**Hikvision UAE**  
T +971-4-4432090  
salesme@hikvision.com

**Hikvision Singapore**  
T +65-6684-4718  
sg@hikvision.com

**Hikvision Spain**  
T +34-91-737-16-55  
info.es@hikvision.com

**Hikvision Tashkent**  
T +99-87-1238-9438  
uzb@hikvision.ru

**Hikvision Hong Kong**  
T +852-2151-1761  
info.hk@hikvision.com

**Hikvision Russia**  
T +7-495-669-67-99  
saleru@hikvision.com

**Hikvision Korea**  
T +82-(0)31-731-8817  
sales.korea@hikvision.com

**Hikvision Poland**  
T +48-22-460-01-50  
info.pl@hikvision.com

**Hikvision Indonesia**  
T +62-21-2933759  
Sales.Indonesia@hikvision.com

**Hikvision Colombia**  
sales.colombia@hikvision.com